



Distance sensor OMT300-R201-IEP-IO-V1



- Medium design with versatile mounting options
- Space-saving distance sensors in small standardized design
- Multi Pixel Technology (MPT) - exact and precise signal evaluation
- IO-Link interface for service and process data
- Analog output 4 ... 20 mA

Distance sensor



Function


The optical sensors in the series are the first devices to offer an end-to-end solution in a medium-sized standard design – from the thru-beam sensor through to the measuring distance sensor. As a result of this design, the sensors are able to perform practically all standard automation tasks.

The entire series enables sensors to communicate via IO-Link.

The DuraBeam laser sensors are durable and can be used in the same way as a standard sensor.

Multi Pixel Technology (MPT) ensures that the standard sensors are flexible and can be adapted to the application environment.

Dimensions



Technical Data

General specifications	
Model	...
Version	...
Manufacturer	...
Year	...
Material	...
Weight	...
Dimensions	...
Power consumption	...
Operating temperature	...
Storage temperature	...
Humidity	...
Shock resistance	...
Vibration resistance	...
Electromagnetic compatibility	...
Environmental protection	...
Compliance	...
Warranty	...
Accessories	...
Documentation	...
Support	...
Training	...
Installation	...
Operation	...
Maintenance	...
Repair	...
Disposal	...
Recycling	...
Energy efficiency	...
Carbon footprint	...
Life cycle cost	...
Return on investment	...
Risk assessment	...
Security	...
Privacy	...
Accessibility	...
Usability	...
Reliability	...
Availability	...
Scalability	...
Flexibility	...
Interoperability	...
Integration	...
Migration	...
Upgrade	...
Upgrade path	...
Upgrade cost	...
Upgrade time	...
Upgrade risk	...
Upgrade success	...
Upgrade impact	...
Upgrade benefits	...
Upgrade challenges	...
Upgrade opportunities	...
Upgrade roadmap	...
Upgrade strategy	...
Upgrade plan	...
Upgrade implementation	...
Upgrade monitoring	...
Upgrade evaluation	...
Upgrade feedback	...
Upgrade communication	...
Upgrade documentation	...
Upgrade support	...
Upgrade training	...
Upgrade testing	...
Upgrade deployment	...
Upgrade rollback	...
Upgrade contingency	...
Upgrade exit strategy	...
Upgrade exit plan	...
Upgrade exit implementation	...
Upgrade exit monitoring	...
Upgrade exit evaluation	...
Upgrade exit feedback	...
Upgrade exit communication	...
Upgrade exit documentation	...
Upgrade exit support	...
Upgrade exit training	...
Upgrade exit testing	...
Upgrade exit deployment	...
Upgrade exit rollback	...
Upgrade exit contingency	...
Upgrade exit exit strategy	...
Upgrade exit exit plan	...
Upgrade exit exit implementation	...
Upgrade exit exit monitoring	...
Upgrade exit exit evaluation	...
Upgrade exit exit feedback	...
Upgrade exit exit communication	...
Upgrade exit exit documentation	...
Upgrade exit exit support	...
Upgrade exit exit training	...
Upgrade exit exit testing	...
Upgrade exit exit deployment	...
Upgrade exit exit rollback	...
Upgrade exit exit contingency	...
Upgrade exit exit exit strategy	...
Upgrade exit exit exit plan	...
Upgrade exit exit exit implementation	...
Upgrade exit exit exit monitoring	...
Upgrade exit exit exit evaluation	...
Upgrade exit exit exit feedback	...
Upgrade exit exit exit communication	...
Upgrade exit exit exit documentation	...
Upgrade exit exit exit support	...
Upgrade exit exit exit training	...
Upgrade exit exit exit testing	...
Upgrade exit exit exit deployment	...
Upgrade exit exit exit rollback	...
Upgrade exit exit exit contingency	...
Upgrade exit exit exit exit strategy	...
Upgrade exit exit exit exit plan	...
Upgrade exit exit exit exit implementation	...
Upgrade exit exit exit exit monitoring	...
Upgrade exit exit exit exit evaluation	...
Upgrade exit exit exit exit feedback	...
Upgrade exit exit exit exit communication	...
Upgrade exit exit exit exit documentation	...
Upgrade exit exit exit exit support	...
Upgrade exit exit exit exit training	...
Upgrade exit exit exit exit testing	...
Upgrade exit exit exit exit deployment	...
Upgrade exit exit exit exit rollback	...
Upgrade exit exit exit exit contingency	...
Upgrade exit exit exit exit exit strategy	...
Upgrade exit exit exit exit exit plan	...
Upgrade exit exit exit exit exit implementation	...
Upgrade exit exit exit exit exit monitoring	...
Upgrade exit exit exit exit exit evaluation	...
Upgrade exit exit exit exit exit feedback	...
Upgrade exit exit exit exit exit communication	...
Upgrade exit exit exit exit exit documentation	...
Upgrade exit exit exit exit exit support	...
Upgrade exit exit exit exit exit training	...
Upgrade exit exit exit exit exit testing	...
Upgrade exit exit exit exit exit deployment	...
Upgrade exit exit exit exit exit rollback	...
Upgrade exit exit exit exit exit contingency	...
Upgrade exit exit exit exit exit exit strategy	...
Upgrade exit exit exit exit exit exit plan	...
Upgrade exit exit exit exit exit exit implementation	...
Upgrade exit exit exit exit exit exit monitoring	...
Upgrade exit exit exit exit exit exit evaluation	...
Upgrade exit exit exit exit exit exit feedback	...
Upgrade exit exit exit exit exit exit communication	...
Upgrade exit exit exit exit exit exit documentation	...
Upgrade exit exit exit exit exit exit support	...
Upgrade exit exit exit exit exit exit training	...
Upgrade exit exit exit exit exit exit testing	...
Upgrade exit exit exit exit exit exit deployment	...
Upgrade exit exit exit exit exit exit rollback	...
Upgrade exit exit exit exit exit exit contingency	...
Upgrade exit exit exit exit exit exit exit strategy	...
Upgrade exit exit exit exit exit exit exit plan	...
Upgrade exit exit exit exit exit exit exit implementation	...
Upgrade exit exit exit exit exit exit exit monitoring	...
Upgrade exit exit exit exit exit exit exit evaluation	...
Upgrade exit exit exit exit exit exit exit feedback	...
Upgrade exit exit exit exit exit exit exit communication	...
Upgrade exit exit exit exit exit exit exit documentation	...
Upgrade exit exit exit exit exit exit exit support	...
Upgrade exit exit exit exit exit exit exit training	...
Upgrade exit exit exit exit exit exit exit testing	...
Upgrade exit exit exit exit exit exit exit deployment	...
Upgrade exit exit exit exit exit exit exit rollback	...
Upgrade exit exit exit exit exit exit exit contingency	...
Upgrade exit exit exit exit exit exit exit exit strategy	...
Upgrade exit exit exit exit exit exit exit exit plan	...
Upgrade exit exit exit exit exit exit exit exit implementation	...
Upgrade exit exit exit exit exit exit exit exit monitoring	...
Upgrade exit exit exit exit exit exit exit exit evaluation	...
Upgrade exit exit exit exit exit exit exit exit feedback	...
Upgrade exit exit exit exit exit exit exit exit communication	...

Measurement range	100 ... 300 mm
Reference target	standard white, 100 mm x 100 mm
Light source	LED
Light type	modulated visible red light
LED risk group labelling	exempt group
Angle deviation	max. +/- 1.5 °
Diameter of the light spot	approx. 8 mm at a distance of 300 mm
Opening angle	1.8 °
Ambient light limit	EN 60947-5-2 : 45000 Lux
Resolution	0.1 mm

Functional safety related parameters

MTTF _d	520 a
Mission Time (T _M)	20 a
Diagnostic Coverage (DC)	0 %

Indicators/operating means

Operation indicator	LED green: constantly on - power on flashing (4Hz) - short circuit flashing with short break (1 Hz) - IO-Link mode
Function indicator	LED yellow: constantly on - switch output active constantly off - switch output inactive

Technical Data


Control elements		Teach-In key
Control elements		5-step rotary switch for operating modes selection
Electrical specifications		
Operating voltage	U_B	18 ... 30 V DC
Ripple		max. 10 %
No-load supply current	I_0	< 25 mA at 24 V supply voltage
Protection class		III
Interface		
Interface type		IO-Link (via C/Q = pin 4)
IO-Link revision		1.1
Device profile		Identification and diagnosis Smart Sensor type 0/type 3.3
Device ID		0x111915 (1120533)
Transfer rate		COM2 (38.4 kBit/s)
Min. cycle time		3 ms
Process data width		Process data input 4 byte Process data output 2 bits
SIO mode support		yes
Compatible master port type		A
Output		
Switching type		The default setting is: C/Q - Pin4: NPN normally open, PNP normally closed, IO-Link I—Pin2: analog output 4...20 mA
Signal output		1 push-pull output , 1 analog output , short-circuit-proof, reverse polarity protection, surge-proof
Switching voltage		max. 30 V DC
Switching current		max. 100 mA , resistive load
Usage category		DC-12 and DC-13
Voltage drop	U_d	≤ 1.5 V DC
Response time		2 ms , see table 1
Analog output		
Output type		1 current output: 4 ... 20 mA
Load resistor		> 1 kΩ voltage output ; ≤ 470 Ω current output
Recovery time		2 ms
Conformity		
Communication interface		IEC 61131-9
Product standard		EN 60947-5-2
Measurement accuracy		
Temperature drift		0.05 %/K
Warm up time		5 min
Repeat accuracy		< 0.5 % , see table 1
Linearity error		0.5 %
Approvals and certificates		
UL approval		E87056 , cULus Listed , class 2 power supply , type rating 1
CCC approval		CCC approval / marking not required for products rated ≤36 V
Ambient conditions		
Ambient temperature		10 ... 50 °C (50 ... 122 °F)
Storage temperature		-40 ... 70 °C (-40 ... 158 °F)
Mechanical specifications		
Housing width		15 mm
Housing height		61.7 mm
Housing depth		41.7 mm
Degree of protection		IP67 / IP69 / IP69K
Connection		4-pin, M12 x 1 connector, 90° rotatable
Material		

Release date: 2023-01-16 Date of issue: 2023-01-16 Filename: 295670-100277_eng.pdf


Technical Data

Housing	PC (Polycarbonate)
Optical face	PMMA
Mass	approx. 47 g

Connection




Connection Assignment



Wire colors in accordance with EN 60947-5-2

1	BN	(brown)
2	WH	(white)
3	BU	(blue)
4	BK	(black)

Assembly



1	Mode rotary switch	
2	Teach-in button	
3	Switching output display Q1	YE
4	Operating indicator	GN

Q1B	Switching output/switch point B
Q1A	Switching output/switch point A
Q2A	Analog output/value A
Q2B	Analog output/value B
0	Keylock

Accessories

	OMH-RL31-02	Mounting bracket narrow
--	--------------------	-------------------------

Accessories

	OMH-RL31-03	Mounting bracket narrow
	OMH-RL31-04	Mounting aid for round steel ø 12 mm or sheet 1.5 mm ... 3 mm
	OMH-RL31-07	Mounting bracket including adjustment
	OMH-R20x-Quick-Mount	Quick mounting accessory
	ICE2-8IOL-G65L-V1D	EtherNet/IP IO-Link master with 8 inputs/outputs
	ICE3-8IOL-G65L-V1D	PROFINET IO IO-Link master with 8 inputs/outputs
	ICE2-8IOL-K45S-RJ45	EtherNet/IP IO-Link master with 8 inputs/outputs, DIN rail, screw terminal
	ICE3-8IOL-K45P-RJ45	PROFINET IO IO-Link master with 8 inputs/outputs, DIN rail, push-in terminals
	ICE3-8IOL-K45S-RJ45	PROFINET IO IO-Link master with 8 inputs/outputs, DIN rail, screw terminal
	IO-Link-Master02-USB	IO-Link master, supply via USB port or separate power supply, LED indicators, M12 plug for sensor connection
	ICE1-8IOL-G30L-V1D	Ethernet IO-Link module with 8 inputs/outputs
	ICE1-8IOL-G60L-V1D	Ethernet IO-Link module with 8 inputs/outputs
	ICE2-8IOL-K45P-RJ45	EtherNet/IP IO-Link master with 8 inputs/outputs, DIN rail, push-in connectors
	V1-G-2M-PUR	Female cordset single-ended M12 straight A-coded, 4-pin, PUR cable grey
	V1-W-2M-PUR	Female cordset single-ended M12 angled A-coded, 4-pin, PUR cable grey

Technical Features

Table 1: Information on Measured Value Filters

Measured value filter						
Filter	1-way	2-way	4-way	16-way	64-way	256-way
Response time (ms)	2	4	8	32	128	512
Repeatability (%)	< 0.5 %					

Settings

Teach-In (TI)

Use the rotary switch for switching signal **Q1** to select the relevant switching threshold A and/or B to teach in.

- The yellow LEDs indicate the current state of the selected output.


To teach in a switching threshold, press and hold the "TI" button for approximately 1 s, until the yellow and green LEDs flash in phase. Teach-in starts when the "TI" button is released.

- Teach-in successful: the yellow and green LEDs flash alternately at 2.5 Hz.
- Teach-in unsuccessful: the yellow and green LEDs quickly flash alternately at 8 Hz.


After an unsuccessful Teach-in, the sensor continues to operate with the previous valid setting after the relevant visual fault signal is issued.

Set switching mode: you can define different switching modes by teaching in the relevant distance data for switching thresholds A and B.

1. Single point mode:



2. Window mode:



Teach in switching thresholds: you can teach in or overwrite a taught-in switching threshold at any time. To do this, press the "TI" button again.

Reset a value: you can reset a taught-in value. To do this, press the "TI" button for > 4 s, until the yellow and green LEDs go out. The reset process itself starts when the "TI" button is released.

- Reset successful: the yellow and green LEDs flash alternately at 2.5 Hz.

Minimum and maximum values for the analog output Q2 are taught in and deleted in the same way as those for the switching output.

The following applies:

A = Minimum voltage/current

B = Maximum voltage/current

Resetting to Factory Settings

To revert back to factory settings, press the "TI" button for > 10 s with the rotary switch set to position "O," until the yellow and green LEDs go out at the same time. The reset process itself starts when the "TI" button is released.

- Reset to factory settings successful: the yellow and green LEDs light up at the same time. The sensor then continues to operate with factory settings.

OMT-IEP

- Factory setting for switching signal Q1:
Switching signal is high active, window mode
- Analog output: current output, 4 mA ... 20 mA absolute mode

OMT-UEP

- Factory setting for switching signal Q1:

Switching signal is high active, window mode

- Analog output: voltage output, 0 V ... 10 V absolute mode

Analog output

The analog output type can be configured as voltage or current output via IO-Link.

The following output types are available:

- Analog output 0 mA ... 20 mA
- Analog output 4 mA ... 20 mA
- Analog output 0 V ... 10 V

The following operating modes are available:


- Absolute mode (default setting)
- Normalized mode
- Rising slope
- Falling slope

The following substitute values can optionally be configured:


- No substitute values used (default setting)
- Substitute value for "no measured value" used
- Substitute value for "no measured value" and "Measuring overrange" used

The sensor's tolerances are based on the digital process data.


Absolute mode (default setting, A and B = deleted)




Normal mode (A and B without teach-in / deleted)



Rising slope (A < B)



Falling slope (A > B)

Configuration

Setting different operating modes via the IO-Link interface

The devices are equipped with an IO-Link interface as standard for diagnostics and parameterization tasks to ensure optimum adjustment of the sensors to the relevant application.

Single point mode operating mode (one switch point):

- "Detection of objects irrespective of type and color in a defined detection range. Objects in the background are suppressed.
- "The switch point corresponds exactly to the set point.



Window mode operating mode (two switch points):

- Detection of objects irrespective of type and color in a defined detection range. Reliable detection when object leaves the detection range.
- Window mode with two switch points.




Center window mode operating mode (one switch point):

- Detection of objects irrespective of type and color in a defined detection range. Sets a defined window around a given object. Objects outside this window are not detected.
- Window mode with one switch point.



Two point mode operating mode (hysteresis operating mode):

- Detection of objects irrespective of type and color between a defined switch-on and switch-off point.



Inactive operating mode:

- Evaluation of switching signals is deactivated.

The associated IODD device description file can be found in the download area at www.pepperl-fuchs.com.